

## Important instructions regarding the internal IEEE 1394 connector

Please note that the internal IEEE 1394 (Firewire) port (PORT3) is shared with the top external connector (PORT2). So that don't use both of these ports at the same time.

## Software installation

### Installation under Windows XP

After Windows XP has booted the card will be installed automatically. Now the message "New Network device installed" appears. If you want to install a FireWire network connection click on the shown symbol and follow the instructions of the Network Setup Wizard. To install the delivered Ulead Video Studio software insert the CD-ROM then click on "Install Ulead VideoStudio..." and follow the instructions shown on the screen. If the installation should not start automatically click on ⇒ **Start** ⇒ **Run...** ⇒ and insert "D:\Autorun.exe" (where **D:** should be the drive letter of your CD-ROM drive).

### Important notes for Windows XP:

You can check if the controller has been installed properly. Click **Start** ⇒ **Control Panel** ⇒ **System** ⇒ **Hardware** ⇒ **Device Manager** (in some cases you have to click on "Switch to classic view" to see the "System" icon). There have to be following entries without a yellow exclamation mark:

#### IEEE 1394 Bus host controller

- NEC OHCI Compliant IEEE 1394 Host Controller

#### Network adapters

- 1394 Net Adapter

### Installation under Windows ME

After boot sequence the "Add New Hardware Wizard" appears and the card will be recognized as "NEC Firewarden OHCI Compliant IEEE 1394 Host Controller". Mark "Automatic search for a better driver (Recommended)" and click on ⇒ **Next** ⇒ Now Windows is copying the needed drivers. Then click on ⇒ **Finish** ⇒ Finally click on ⇒ **Yes** ⇒ to restart the computer. To install the delivered Ulead Video Studio software insert the CD-ROM then click on "Install Ulead VideoStudio..." and follow the instructions shown on the screen. If the installation should not start automatically click on ⇒ **Start** ⇒ **Run...** ⇒ and insert "D:\Autorun.exe" (where **D:** should be the drive letter of your CD-ROM drive).

### Important notes for Windows ME:

You can check if the controller has been installed properly. Click **Start** ⇒ **Settings** ⇒ **Control Panel** ⇒ **System** ⇒ **Device Manager** (in some cases you have to click on "view all Control Panel options." to see the "System" icon).

There have to be following entries without a yellow exclamation mark:

#### 1394 Bus Controller

- NEC Firewarden OHCI compliant IEEE 1394 Host Controller

#### Network adapters

- NDIS 1394 Net Adapter

### Installation under Windows 98 SE:

After the boot sequence the "Add New Hardware Wizard" appears and the card will be recognized as "NEC Firewarden OHCI Compliant IEEE 1394 Host Controller". Click on ⇒ **Next** ⇒ Now mark "Search for the best driver for your device (Recommended)". ⇒ **Next** ⇒ Do not mark any of the shown check boxes and click on ⇒ **Next** ⇒ **Next** ⇒ **Next** ⇒ In some cases you have to insert now the Windows 98 CD-ROM. Do this and click on "OK". Now Windows is copying the needed drivers. After this click on ⇒ **Finish** ⇒ Now remove the CD-ROM from the drive and restart your computer system. To install the delivered Ulead Video Studio software insert the CD-ROM then click on "Install Ulead VideoStudio..." and follow the instructions shown on the screen. If the installation should not start automatically click on ⇒ **Start** ⇒ **Run...** ⇒ and insert "D:\Autorun.exe" (where **D:** should be the drive letter of your CD-ROM drive).

### Important notes for Windows 98/SE:

You can check if the controller has been installed properly. Click **Start** ⇒ **Settings** ⇒ **Control Panel** ⇒ **System** ⇒ **Device Manager**. There have to be following entries without a yellow exclamation mark:

#### 1394 Bus Controller

- NEC Firewarden OHCI Compliant IEEE 1394 Host Controller

### Installation under Windows 2000:

With Windows 2000 the 2-port FireWire Kit will be installed automatically. To install the delivered Ulead Video Studio software insert the CD-ROM then click on "Install Ulead VideoStudio..." and follow the instructions shown on the screen. If the installation should not start automatically click on ⇒ **Start** ⇒ **Run...** ⇒ and insert "D:\Autorun.exe" (where **D:** should be the drive letter of your CD-ROM drive).

### Important notes for Windows 2000:

You can check if the controller has been installed properly. Click **Start** ⇒ **Settings** ⇒ **Control Panel** ⇒ **System** ⇒ **Hardware** ⇒ **Device Manager**. There have to be following entries without a yellow exclamation mark:

#### IEEE 1394 Bus host controllers

- NEC OHCI Compliant IEEE 1394 Host Controller